

## Utility Boxes and Covers

								
<b>CI1141</b>	<b>BC1110</b>	<b>CI1110-SB</b>	<b>BC1110-LSKO</b>					
								
<b>BC1110-SSX</b>	<b>BC1110-R</b>	<b>1151</b> (For toggle switch)	<b>1198</b> (For Decora or GFCI)	<b>1199</b> (For duplex receptacle)				
								
<b>BC11-C-1</b>	<b>BC11-C-2</b>	<b>BC11-C-3</b>	<b>BC11-C-4</b>	<b>BC11-C-5</b>	<b>BC11-C-10</b>	<b>CI11-C-10-HV</b>	<b>BC11-C-4-HV</b>	<b>BC11-C-5-HV</b>



Cat. No.	Volume (Cu. in.)	Features		Knockouts		
		Bracket	Raised Ground Screw	1/2 in. ends	1/2 in. bottom	1/2 in. sides
<b>1-1/2 in. Deep – 4 in. x 2-1/4 in.</b>						
<b>CI1141</b>	13.0	mounting ears	no	2	2	6
<b>1-7/8 in. Deep – 4 in. x 2-3/8 in.</b>						
<b>BC1110</b>	16.5	-	yes	2	2	6
<b>CI1110-SB</b>	16.5	“SB”	yes	2	2	3
<b>BC1110-R</b>	16.5	-	-	2	-	6
<b>2-1/8 in. Deep – 4 in. x 2-1/2 in.</b>						
<b>1151</b>	18.5	-	yes	2	2	-
<b>1198</b>	18.5	-	yes	2	2	-
<b>1199</b>	18.5	-	yes	2	2	-
<b>1-7/8 in. Deep – 4 in. x 2-3/8 in.</b>						
<b>BC1110-LSKO</b>	16.5	-	yes	2	2	-
<b>BC1110-SSX</b>	16.5	“SSX”	yes	2	2	-

Cat. No.	Description	Cat. No.	Description
<b>Covers – 11 Series</b>			
<b>BC11-C-1</b>	For duplex receptacle	<b>BC11-C-10</b>	Decora/GFCI
<b>BC11-C-2</b>	For 1-19/32 in. diameter 20 A single locking receptacle	<b>CI11-C-10-HV</b>	Decora 347 V
<b>BC11-C-3</b>	For 1-13/32 in. diameter 15 A single receptacle	<b>BC11-C-4-HV</b>	Blank 347 V
<b>BC11-C-4</b>	Blank	<b>BC11-C-5-HV</b>	For toggle switch
<b>BC11-C-5</b>	For toggle switch		

Note: Covers: Device mounting screws included