

### Overview




The RCoax cables are radiating cables that function as special antennas for the SCALANCE W Access Points in environments with complex radio coverage. Its design means that a defined, cone-shaped radio field is generated along the RCoax cable. The radiating cables are therefore perfectly suitable for use in all types of applications with track-bound vehicles.

- Rugged coaxial cable which can be easily installed
- Two cables for use in the frequency bands 2.4 GHz and 5 GHz
- Connection as external antenna to SCALANCE W780 Access Points
- Connection of mobile nodes via SCALANCE W740 Client Modules and IWLAN/PB Link PN IO using an antenna aligned to the RCoax
- Suitable for use in hazardous areas (Zone 2); no special approvals necessary

### Design

The RCoax cables were specially designed for the frequency band around 2.4 GHz or 5 GHz respectively.



### Ordering data

### Order No.

#### IWLAN RCoax cables

Radiating cable for complex radio environments as special antenna for SCALANCE W Access Points; for extended temperature range (-40 °C to + 85 °C); sold by the meter  
minimum order quantity 20 m

- 2.4 GHz
- 5 GHz

**6XV1 875-2A**  
**6XV1 875-2D**

#### Accessories

#### IWLAN RCoax N-Connect stripping tool

Stripping tool for fast stripping of RCoax cable on site

**6GK1 901-1PH00**

#### RCoax N-Connect female N-connector

Plug connector for assembly on site; connection unit of RCoax cable for connection of further components, N-female connection.

**6GK5 798-0CN00-0AA0**

#### RCoax N-Connect male/male Coupler

RF coupling for connecting an RCoax antenna to an RCoax cable; two N-Connect male connectors

**6GK5 798-0CP00-1AA0**

#### IWLAN RCoax cable clip 1/2"

Cable holder for RCoax cable

- 10 items
- 100 items

**6GK5 798-8MB00-0AC1**  
**6GK5 798-8MB00-0AM1**

#### IWLAN RCoax threaded washer M6

Threaded washer M6 for RCoax cable clip 1/2", for assembly with M6 threaded bolts

- 10 items
- 100 items

**6GK5 798-8MC00-0AC1**  
**6GK5 798-8MC00-0AM1**

#### IWLAN RCoax spacer 85 mm

Spacer 85 mm for RCoax cable clip 1/2"

- 10 items
- 100 items

**6GK5 798-8MD00-0AC1**  
**6GK5 798-8MD00-0AM1**

### More information

#### Wireless approvals:

Current approvals can be found on the Internet at:  
[www.siemens.com/wireless-approvals](http://www.siemens.com/wireless-approvals)

To assist in selecting the right products for Industrial Wireless Communication, the SIMATIC NET Selection Tool is available:

Online version:  
[www.siemens.com/snst](http://www.siemens.com/snst)

Offline version:  
[www.siemens.com/snst-download](http://www.siemens.com/snst-download)